

# SENCI Datasheet - SC4000ED-3.0KW (LPG)



**ACI Motors**



Brand & Model	<b>SENCI, SC4000ED</b>
Rated Output	3.2KW / 2.7KW (LPG)
Max. Output	3.5KW / 3.0KW (LPG)
Volts	220v
Frequency	50Hz
Engine RPM	3000
Power Factor	1
Max. output (Amp)	14
Starting System	E-start
Country of Origin	<b>CHINA</b>

### Generator Features :

- \* SENCi, SV230L Engine , Durable & High performance
- \* 4-Stroke OHV Single-Cylinder Engine
- \* Maintenance free **Brushless Alternator**
- \* Sound Level 65dBA ISO3744 Certified
- \* Volts, Hertz and Hour monitor ( 3 in 1 )
- \* Easier 'on' & 'off' of AC output with circuit breaker
- \* Easy to Carry & Cold Protection Frame

Alternator General Data	
Brand	SENCI
Alternator Type	Brushless
Voltage Regulator	Capacitor
Number of Phase	1
Protection System	AC Circuit Breaker

Engine General Data	
Engine Brand	SENCI SV230L
Engine Type	4-stroke OHV
Fuel	Gasoline
Fuel Tank Capacity	15L
Cooling System	Air Cooled
Displacement /HP	223cc, 7.5hp
Ignition System	T.C.I
Engine oil Capacity	600ml

Generator Dimension and Noise Level	
Length	600mm
Width	465mm
Height	475mm
Weight (KG)	54kg
Sound @7m (dBA)	<97

Fuel Consumption	
Fuel Consumption @100% Load (L/H)	1.8L
Fuel Consumption @75% Load (L/H)	1.5L
Fuel Consumption @50% Load (L/H)	0.6L
Continuous Duration of Runs (H)	7.5h

**Contact us:**

**ACI Motors Ltd.**

**Email:** info@aci-bd.com **Web:** www.acimotors-bd.com

**Contact: 01324732639**

**Head office :**

ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626