

Senci Portable Generator -SK10000



ACI Motors



Brand & Model	SENCI, SK10000
Prime Output	8.0KVA / 8.0KW
Standby Output	8.5kVA / 8.5KW
Volts	220 v
Frequency	50 Hz
Engine RPM	3000
Power Factor	1
Max. output (Amp.)	38.6
Starting System	Electric & Recoil
Country of Made	CHINA

Generator Features :

- * SENCi-SK10000 Durable & High performance
- * 4-Stroke OHV Single-Cylinder Engine
- * 100% Copper **Brush Alternator**
- * Sound Level 74 dBA ISO3744 Certified
- * Volts, Hertz and Hour monitor (3 in 1)
- * Easier 'on' & 'off' of AC output with circuit breaker
- * Easy to Carry & Cold Protection Frame

Alternator General Data	
Brand	SENCI
Type	COPPER
Pole	2 Poles
Voltage Regulator	AVR
Number of Phase	Single Phase
Protection	AC Circuit Breaker

Engine General Data	
Engine Brand	SENCI
Model	SC460
Engine Type	4-Stroke,OHV
Number of Cylinder	Single (1)
Fuel	Petrol / Octane
Fuel Tank Capacity	25
Cooling System	Air Cooled
Displacement /HP	459cc/12HP
Ignition System	T.C.I
Engine oil Capacity	1.1L

Generator Dimension and Noise Level	
Length	698 mm
Width	535 mm
Height	550 mm
Weight (KG)	86
Sound @7m (dBA)	74

Fuel Consumption	
Fuel Consumption @100% Load (L/H)	3.5
Fuel Consumption @75% Load (L/H)	2.6
Fuel Consumption @50% Load (L/H)	1.7
Continuous Duration of Runs (H)	7.1

Contact us:

ACI Motors Ltd.

Email: al.abdullah@aci-bd.com **Web:** www.acimotors-bd.com

Contact: 01324732639

Head office :

ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626