

## SENCI Portable Genertor - SK5500E - 5.0 KVA / KW



Brand & Model	<b>SENCI, SK5500E</b>
Rated Output	5.0kVA / 5,000Watt
Max. Output	5.5kVA / 5,500Watt
Volts	220v
Frequency	50Hz
Engine RPM	3000
Power Factor	1
Max. output (Amp)	10A
Starting System	E-start
Country of Origin	<b>CHINA</b>

### Generator Features :

- \* SENCi, SK5500E Engine , Durable & High performance
- \* 4-Stroke OHV Single-Cylinder Engine
- \* Maintenance free **Brushless Alternator**
- \* Sound Level 65dBA ISO3744 Certified
- \* Volts, Hertz and Hour monitor ( 3 in 1 )
- \* Easier 'on' & 'off' of AC output with circuit breaker
- \* Easy to Carry & Cold Protection Frame

### Alternator General Data

Brand	SENCI
Alternator Type	Brushless
Voltage Regulator	Capacitor
Number of Phase	1
Protection System	AC Circuit Breaker

### Engine General Data

Engine Brand	SENCI
Model	AP190
Engine Type	4-stroke OHV
Fuel	Gasoline
Fuel Tank Capacity	25L
Cooling System	Air Cooled
Displacement /HP	420cc,11HP
Ignition System	T.C.I
Engine oil Capacity	1.1L

### Generator Dimension and Noise Level

Length	695mm
Width	530mm
Height	555mm
Weight (KG)	80kg
Sound @7m (dBA)	72

### Fuel Consumption

Fuel Consumption @100% Load (L/H)	2.0L/h
Fuel Consumption @75% Load (L/H)	0.8L
Fuel Consumption @50% Load (L/H)	0.6L
Continuous Duration of Runs (H)	9h

#### Contact us:

**ACI Motors Ltd.**

**Email:** info@aci-bd.com **Web:** www.acimotors-bd.com

**Contact: 01324732639**

**Head office :**

ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626