

SENCI Portable Generator SK6500



ACI Motors



Brand & Model	SENCI, SK6500
Rated Output	6.5kVA / 6,500Watt
Max. Output	6.8kVA / 6,800Watt
Volts	220v
Frequency	50Hz
Engine RPM	3,000
Power Factor	1
Max. output (Amp)	30A
Starting System	E-start
Country of Made	CHINA

Generator Features :

- * SENCi,SK6500 Durable & High performance
- * 4-Stroke OHV Single-Cylinder Engine
- * 100% Copper **Brush Alternator**
- * Sound Level 70 dBA ISO3744 Certified
- * Volts, Hertz and Hour monitor (3 in 1)
- * Easier 'on' & 'off' of AC output with circuit breaker
- * Easy to Carry & Cold Protection Frame

Alternator General Data	
Brand	SENCI
Alternator Type	Copper
Voltage Regulator	AVR
Number of Phase	1
Protection System	AC Circuit Breaker
Ignition System	T.C.I

Engine General Data	
Engine Brand	SENCI
Model	SC460/192
Engine Type	4-stroke OHV
Fuel	Gasoline (Petrol / Octane)
Fuel Tank Capacity	25L
Cooling System	Air Cooled
Engine Displacement	459cc
Engine HP	16HP
Engine oil Capacity	1.1L

Generator Dimension and Noise Level	
Length	695mm
Width	530mm
Height	555mm
Weight (KG)	84kg
Sound @7m (dBA)	74

Fuel Consumption	
Fuel Consumption @100% Load (L/H)	2.5 L/h
Fuel Consumption @75% Load (L/H)	2.0 L/H
Fuel Consumption @50% Load (L/H)	1.5 L/H
Continuous Duration of Runs (H)	10 h

Contact us:

ACI Motors Ltd.

Email: info@aci-bd.com **Web:** www.acimotors-bd.com

Contact: 01324732639

Head office :

ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626