

Senci Portable Generator -SK10000



ACI Motors



Brand & Model	SENCI, SK10000
Prime Output	8.0KVA / 8.0KW
Standby Output	8.5kVA / 8.5KW
Volts	220 v
Frequency	50 Hz
Engine RPM	3000
Power Factor	1
Max. output (Amp.)	38.6
Starting System	Electric & Recoil
Country of Made	CHINA

Generator Features :

- * SENCi-SK10000 Durable & High performance
- * 4-Stroke OHV Single-Cylinder Engine
- * 100% Copper **Brush Alternator**
- * Sound Level 74 dBA ISO3744 Certified
- * Volts, Hertz and Hour monitor (3 in 1)
- * Easier 'on' & 'off' of AC output with circuit breaker
- * Easy to Carry & Cold Protection Frame

Alternator General Data

Brand	SENCI
Type	COPPER
Pole	2 Poles
Voltage Regulator	AVR
Number of Phase	Single Phase
Protection	AC Circuit Breaker

Generator Dimension and Noise Level

Length	698 mm
Width	535 mm
Height	550 mm
Weight (KG)	86
Sound @7m (dBA)	74

Engine General Data

Engine Brand	SENCI
Model	SC460
Engine Type	4-Stroke,OHV
Number of Cylinder	Single (1)
Fuel	Petrol / Octane
Fuel Tank Capacity	25
Cooling System	Air Cooled
Displacement /HP	459cc/12HP
Ignition System	T.C.I
Engine oil Capacity	1.1L

Fuel Consumption

Fuel Consumption @100% Load (L/H)	4.16L/H
Fuel Consumption @75% Load (L/H)	3.33L/H
Fuel Consumption @50% Load (L/H)	2.63L/H
Continuous Duration of Runs (H)	7.1

Contact us:

ACI Motors Ltd.

Email: al.abdullah@aci-bd.com **Web:** www.acimotors-bd.com

Contact: 01324732639

Head office :

ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626