

SENCI Datasheet - SK2500E - 2.5kW



Brand & Model	SENCI, SK2500E
Rated Output	2.0kVA / 2,000Watt
Max. Output	2.2kVA / 2,200Watt
Volts	220v
Frequency	50Hz
Engine RPM	3000
Power Factor	1
Max. output (Amp)	10A
Starting System	E-start
Country of Origin	CHINA

Generator Features :

- * SENCi, SK2500E Engine , Durable & High performance
- * 4-Stroke OHV Single-Cylinder Engine
- * Sound Level 65dBA ISO3744 Certified
- * Volts, Hertz and Hour monitor (3 in 1)
- * Easier 'on' & 'off' of AC output with circuit breaker
- * Easy to Carry & Solid Protection Frame

Alternator General Data	
Brand	SENCI
Alternator Type	Copper
Voltage Regulator	AVR
Number of Phase	1
Protection System	AC Circuit Breaker

Engine General Data	
Engine Brand	SENCI
Model	AP190
Engine Type	4-stroke OHV
Fuel	Gasoline
Fuel Tank Capacity	15L
Cooling System	Air Cooled
Displacement /HP	208cc,5.5HP
Ignition System	T.C.I
Engine oil Capacity	600ml

Generator Dimension and Noise Level	
Length	600mm
Width	465mm
Height	475mm
Weight (KG)	44kg
Sound @7m (dBA)	65

Fuel Consumption	
Fuel Consumption @100% Load (L/H)	1.43L/H
Fuel Consumption @75% Load (L/H)	1.15L/H
Fuel Consumption @50% Load (L/H)	0.88L/H
Continuous Duration of Runs (H)	10.5h

Contact us:

ACI Motors Ltd.

Email: info@aci-bd.com **Web:** www.acimotors-bd.com

Contact: 01324732639

Head office :

ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626