SENCI Datasheet - SK4500E- 3.5kVA

Brand & Model	**SENCI, SK4500E**
Rated Output	3.2kVA / 3,200Watt
Max. Output	3.5kVA / 3,500Watt
Volts	220v
Frequency	50Hz
Engine RPM	3000
Power Factor	1
Max. output (Amp)	16
Starting System	E-start
Country of Origin	**CHINA**

Generator Features :

* SENCI, SK4500E Engine , Durable & High performance
* 4-Storke OHV Single-Cylinder Engine
* Maintanance free **Brushless Alternator**
* Sound Level 65dBA ISO3744 Certified
* Volts, Hertz and Hour monitor (3 in 1)
* Easier 'on' & 'off' of AC output with circuit breaker
* Easy to Carry & Colid Crotection Frame

Alternator General Data	
Brand	SENCI
Alternator Type	Brushless
Voltage Regulator	Capacitor
Number of Phase	1
Protection System	AC Circuit Breaker

Engine General Data	
Engine Brand	SENCI
Engine Type	4-stroke OHV
Fuel	Gasoline
Fuel Tank Capacity	15L
Cooling System	Air Cooled
Displacement /HP	223cc, 7.5hp
Ignition System	T.C.I
Engine oil Capacity	600ml

Generator Dimension and Noise Level	
Length	600mm
Width	465mm
Height	475mm
Weight (KG)	54kg
Sound @7m (dBA)	65

Fuel Consumption	
Fuel Consumption @100% Load (L/H)	2.0L/H
Fuel Consumption @75% Load (L/H)	1.66L/H
Fuel Consumption @50% Load (L/H)	1.25L/H
Continuous Duration of Runs (H)	7.5h

Contact us:
ACI Motors Ltd.
Email: info@aci-bd.com **Web:** www.acimotors-bd.com
Contact: 01324732639
Head office :
ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626